



## Temporary Power Centers with GFCI Protection

50A Input  
20A, 30A, 50A Output  
120/240V/AC (Max.)


### Temporary Power Centers

#### RhinoBox NEMA 3R



RB300M

Rating A	V/AC	Distribution Devices	Receptacle Rating	Protection Overload	GFCI	Catalog No.*	
50 (Max.)	120/240	(6) WR Duplex Receptacles	20A, 125V	✓	✓	<input type="checkbox"/> RB300M	
		(1) Locking Receptacle	30A, 250V	✓	-		
		(1) Locking Inlet	50A, 125/250V	-	-		
		(1) Locking Outlet	50A, 125/250V	-	-		
50 (Max.)	120/240	(6) Single Receptacles	20A, 125V	✓	✓	<input type="checkbox"/> RB301M	
		(1) Locking Receptacle	30A, 250V	✓	-		
		(1) Locking Inlet	50A, 125/250V	-	-		
		(1) Locking Outlet	50A, 125/250V	-	-		
50 (Max.)	120/240	(6) Locking Receptacles	20A, 125V	✓	✓	<input type="checkbox"/> RB302M	
		(1) Locking Receptacle	30A, 250V	✓	-		
		(1) Locking Inlet	50A, 125/250V	-	-		
		(1) Locking Outlet	50A, 125/250V	-	-		
50 (Max.)	120/240	(3) Single Receptacles	20A, 125V	✓	✓	<input type="checkbox"/> RB303M	
		(3) Locking Receptacles	20A, 125V	✓	✓		
		(1) Locking Receptacle	30A, 250V	✓	-		
		(1) Locking Inlet	50A, 125/250V	-	-		
		(1) Locking Outlet	50A, 125/250V	-	-		
50 (Max.)	120/240	(7) WR Duplex Receptacles	20A, 125V	✓	✓	<input type="checkbox"/> RB3001M	
		(1) Locking Inlet	50A, 125/250V	-	-		
		(1) Locking Outlet	50A, 125/250V	-	-		
50 (Max.)	120/240	(7) Locking Receptacles	20A, 125V	✓	✓	<input type="checkbox"/> RB3021M	
		(1) Locking Inlet	50A, 125/250V	-	-		
		(1) Locking Outlet	50A, 125/250V	-	-		



\*Automatic GFCI reset configurations are available. When ordering automatic GFCI reset RhinoBox replace "M" in Catalog No. with "A". Example: RB300A = Automatic; RB300M = Manual.

NEMA 1 configurations are available. To order, replace "3" in Catalog No. with "2" for NEMA 1 enclosure. Example: RB300M = NEMA 3R; RB200M = NEMA 1.

#### Specification Information:

RhinoBox: L-11

#### Icon Key

NAFTA Compliant - see page O-30